





DC TO AC POWER INVERTER

AH SERIES PM-A-0350AH



| Model No. | PM-A-0350AH-12 | PM-A-0350AH-24 |
|---|---|---|
| Output power continuous | 350W | 350W |
| Instant Surge | 700W | 700W |
| AC Output Voltage | 100V/110V/115V/120Vac or 220V/230V/240Vac | 100V/110V/115V/120Vac or 220V/230V/240Vac |
| Regulation | ± 5~10% | ± 5~10% |
| DC Input Voltage | 10~15V | 20~30V |
| Low Battery Alarm & Shut-Down | 10.5V ±0.5VDC & 10V ±0.5VDC | 21V ±0.8VDC & 20V ±0.8VDC |
| Input Low Voltage Protection | Yes | Yes |
| Reverse Polarity Protection | Yes | Yes |
| Soft Start | Yes | Yes |
| DC/AC Isolated | Yes | Yes |
| AVR Design | Yes | Yes |
| Output Short Circuit Protection | Yes | Yes |
| Overload Protection | Yes | Yes |
| Auto Temperature Control Fan | Yes | Yes |
| Remote Control | No | No |
| Temperature protection | 50°C ± 5°C | 50°C ± 5°C |
| Output frequency | 50Hz or 60Hz ± 3% | 50Hz or 60Hz ± 3% |
| Efficiency | >85% | >85% |
| No Load Current | <0.25A | <0.25A |
| Dimensions (L x W x H mm) | 190 * 102 * 63 | 190 * 102 * 63 |
| Net weight (by Kg/s) | 1.2 | 1.2 |
| Accessory | Cigar Plug & Clip | Cigar Plug & Clip |
| Output Waveform (Modified sine wave) |  |  |

Power Master technology co., ltd.

8F, 651~3 Chung-Cheng Rd. Shin-Chuang City, Taipei County, Taiwan, R.O.C.
Telephone No: 886-2-6626-6660, Fax No: 886-2-6626-6800

E-mail: sales@powermaster.com.tw, <http://www.powermaster.com.tw> &
<http://inverters.powermaster.com.tw> & www.b2binverters.com